
# INTELLIGENT FURNITURE SMART FINGERPRINT LOCK




**USER MANUAL** 

### INSTALLATION INSTRUCTION

### Step1: To install the front panel and lock case

1)Paste the drawing on the door at proper height, the distance is appro-40MM between centre hole and opening wall, then drill the hole accordingly. See picture 1

# wire connection




Picture 1

- Insert connecting wire (See picture 2) into the front panel, then wire goes through the centre hole; fix up the panel by screw M4X25
  Insert connection wire (See Picture 2) into lock case, then fix up by
- screw ST3.5X16MM. Make sure the distance is 40MM between the centre of lock case and opening wall

### Step 2 Install the striking plate


Fix up the striking plate by screw ST3.5X20. Make sure it can catch the latch of lock case and lock the door. The distance is appro. 20.5MM



### COMPONENT



# Installation Ceiling Panel



Screw Cut off the page and paste it on the door, then drill the hole according to the drawing

# **USER INSTRUCTION**

### Feature

- Access control: fingerprint
- 2. Advanced Biometric technology for better response and sensitivity
- 3. Add up to 20 fingerprint
- Automatic motorized mechanism
- 5.Large light indicator with visual signal
- 6. Operates with 3 AAA alkaline batteries, batteries life time up to 1 year.
- 7. Widely used in drawer, cabinet, wardrobe etc.

### Step 1 Select Operation Mode

- → Press reset button for 4 sec, four (4) beeps, then keep holding two (2) beeps, release
- → Mode changed, all the fingerprint clear off

- Automatic Mode: Latch stretches out in 4 sec after opened
- ☆ Manual Mode: Latch keeps inside the box after opened
- Automatic mode and manual mode change in turn, automatic mode in factory setting

### Step 2 Register new fingerprint

- → Press reset button then release, a (1) beep,blue light on
- → Put a finger on the reader, a (1) beep then remove; same operation for
- → Light turn into green with two (2) beeps, fingerprint registered.
- → If any mistakes, indicator in red with three (3) beeps. Try again.

## Note:

- ☆ Same operation to add more fingerprint. It can register 20 fingerprint, more than 20 ones, the system will log off. If new fingerprint needed, clear up all the fingerprint first.
- Any finger can open the lock before registered one, ensure register the fingerprint before using.
- ☆ Ensure the lock works well, it's better to add no less than 3 different. fingerprint to register. When registering, put on the finger as the following maps

### Step 3 Remove all the fingerprint

- → Press reset button for 4 sec, four (4) beeps then all the fingerprint removed
- ☆ Ensure the belong safety, clear up all the fingerprint before using Step 4 Lock and Unlock

### 1. Automatic Mode

- →Push the door closed and door locks automatically
- →Put valid finger on the reader
- →Indicator in green, two (2) beeps, door unlocked, then pull door open

### 2. Manual Mode

- →Push the door closed, then put valid fingerprint on the reader.Latch stretches out, two (2) beeps, door locks
- →Put valid finger on the reader
- →Indicator in green, two (2) beeps, door unlocked, then pull door open

### Low Battery Warning

Six (6) beeps after opened indicates low battery, please replace the battery immediately. If the battery can't open the door, enter outer power supply by USB port to open the lock.